### O ICOM

**VHF MARINE TRANSCEIVER** 



SHIP A SHIP TYPE : CARGO STATUS : UNDERWAY SPEED / COURSE : 12.5KT/271° LENGTH × BEAM : 76M × 12M DRAUGHT : 3M

SHIP B SHIP TYPE : OTHER STATUS : UNDERWAY SPEED / COURSE : 9.4KT/41° LENGTH × BEAM : 149M × 30M DRAUGHT : 4.7M

SHIP C SHIP TYPE : PASSENGER STATUS : UNDERWAY SPEED / COURSE : 8.8KT/185° LENGTH × BEAM : 62M × 13M DRAUGHT : 3M

CH

ENT

CH

CLEAR



12.

-

H/1

# Fixed Mount VHF and AIS Receiver C with NMEA 2000<sup>™</sup> Connectivity



#### Integrated AIS Receiver\*

With an integrated AIS receiver, the IC-M506 can show real-time AIS vessel traffic information on the display. The AIS target call function allows you to easily set up a DSC individual call. The Plotter, Target list and Danger list can be toggled on the display.



E TARGET LIST	(	139) 🗄
MMSI/Name	RNG	BRG
431003158	1.1	331
TAMAKI PRIN	1.4	003
EIWAMARU	1.4	280
OVAL LP NO.1	1.6	266
KANRYUMARU	1.7	006
(NICO)		

AIS plotter display

Target list example



#### NMEA 2000<sup>™</sup> Connectivity\*

With the plug-and-play functionality of NMEA 2000, the IC-M506 can easily connect to a NMEA 2000 network. The IC-M506 can receive and transmit GPS (position, course (COG) and speed (SOG)), AIS report and DSC call information data and transmit radio frequency and PGN list data on the network. Using this function, the IC-M506 can convert NMEA 0183 GPS data to NMEA 2000 data for other equipment.



#### Last Call Voice Recording

The last call voice recording function automatically saves the last two minutes of the last incoming call. You can replay the received call, and not miss any incoming call.



#### Active Noise Cancelling

Using digital signal processing technology, the built-in bidirectional active noise cancelling provides superb performance. It reduces background noise to up to 90% in the received signal and 30% fixed in the transmitting signal. The function OFF setting is also possible.



#### **Intuitive Menu-Driven User Interface**

The intuitive software key functions provide easy and

fast operation to control the multiple functions of the IC-M506. The bottom line of the dot-matrix display shows the software key functions which can be toggled with the left and right buttons.



Functions menu



#### 25W Two-Way Hailer

When connected to an external hailer horn, you can talk to people on the deck or shore from the radio's microphone and can hear people's reply via the hailer speaker. The RX hailer function allows you to monitor the received audio from the hailer horn. The built-in 25W amplifier increases your talk power, making it loud and clear.



#### Built-in Horn (Automatic & Manual)

Foghorn feature is built-in via the external Hailer horn. Four horn patterns are selectable for the automatic horn function.



# ombo



#### ITU Class D DSC (Meets ITU-R M493-13)

The built-in DSC watch function monitors Ch. 70 (DSC channel) activity, even while you are receiving another channel. DSC functions include: distress, individual, group, all ships, urgency, safety, position request/report, polling request and DSC test calls. Up to 100 DSC address IDs can be programmed.

#### **Rear Microphone Version\***

With this version, the microphone connector is drawn from the rear panel and a 6.1m (20ft) microphone extension cable

is supplied to allow you clean and neat panel installation.

\* Ask your dealer for details.

#### **IPX8 Submersible Plus<sup>™</sup>**

The IC-M506 and supplied HM-205B/RB microphone can withstand 1m (3.2ft) depth of water for 60 minutes.

#### **Other Features**

- Auto and manual foghorn function
- Simple remote control speaker-microphone, HM-205B/RB
- 15W audio output power (with external speaker)
- Weather channels with alert function (USA version only)
- AquaQuake<sup>™</sup> draining function
- Optional voice scrambler, UT-112 for private conversation
- MA-500TR AIS transponder and MarineCommander™ compatible

\* AIS receiver and NMEA 2000 interface units are options, depending on version.

#### Optional COMMANDMIC<sup>™</sup> for 2nd Station Capability



#### Full Control and Intercom

The optional COMMANDMIC, HM-195B/ SW provides 2nd station capability for using the IC-M506 from up to 18.3m (60ft)\* away such as a separate cabin or tower. Most functions including DSC and AIS functions can be controlled from the COM-MANDMIC and can be used as an intercom with the IC-M506.

\* Two optional OPC-1541 extension cables required.

#### IPX7 SUBMERSIBLE

**IPX7 Submersible Construction** The HM-195B/SW withstands submersion





#### Same Menu-Driven User Interface with IC-M506

The HM-195B/SW provides same user interface with the IC-M506. The directional keypad and softkey buttons allow you to perform various operations and settings. The audio and backlight levels can be set independently from the IC-M506.

#### Other Features

- External speaker connection
- Black and super white color version
- Remote power ON/OFF function
- One COMMANDMIC can be used

"Distress" button on the back of the unit

їсом

COMMANDMIC



#### VHF MARINE TRANSCEIVER

#### SPECIFICATIONS

GENERALIFrequency rangeTx $Rx$ $156.025-157.425MHz$ Rx $156.025-157.425MHz$ $156.525MHz$ AIS1, 2 $161.975$ , $162.025MHz$ Usable channelsUSA, CAN, INT, WXchannelsUSA, CAN, INT, WXchannels $16K0G3E$ (FM),Type of emission $16K0G3E$ (FM), $16K0G2B$ (DSC)Power supply requirement $13.8V$ DC $11.7-15.9V$ DC)Current drain (at $13.8V$ DC) $5.5A$ $5.4$ $5.0A$ (RX hailer ON) $11.8V$ DC $1.5A$ Operating temperature range $-20^{\circ}C$ to $+60^{\circ}C$ ; $-4^{\circ}F$ to $+140^{\circ}F$ Antenna impedance $50\Omega$ (SO-239)Weight (approx.) $1400g$ ; $3.09lb$ TRANSMITTEROutput power (at $13.8V$ DC) $25W$ , $1W$ Max. frequency deviation $\pm 5.0kHz$ Frequency tolerance $\pm 10ppm$ Spurious emissionsLess than $-70dBc$ (at $25W$ )Residual modulationMore than 70dBRECEIVERIntermediate frequency CH70Intermediate frequency CH70 (1% BER)More than 75dB More than 73dBµ emfAdjacent channel Selectivity (At 12dB SINAD) $0.22\muV$ typicalAdjacent channel CH70 (1% BER)More than 75dB More than 68dBµ emfHum and noiseMore than 15W with a 4 $\Omega$ RX speaker			
Rx CH70 AIS1, 2156.050-163.275MHz 156.525MHzUsable channelsUSA, CAN, INT, WX channelsType of emission16K0G3E (FM), 16K0G2B (DSC)Power supply requirement13.8V DC (11.7-15.9V DC)Current drain (at 13.8V DC) Tx 25W output5.5A 5.0A (RX hailer ON)Tx Z5W output Internal SP5.5AOperating temperature range Internal SP-20°C to +60°C; -4°F to +140°FAntenna impedance50Q (SO-239)Weight (approx.)1400g; 3.09lbTRANSMITTER25W, 1WOutput power (at 13.8V DC)25W, 1WSpurious emissionsLess than -70dBc (at 25W)Residual modulationMore than 70dBRECEIVERInternel powerIntermediate frequency CH70 (1% BER)1st 30.15MHz, 2nd 450kHz st 21.7MHz, 2nd 450kHzSpurious response CH70 (1% BER)More than 73dBµ emfIntermodulationMore than 75dB More than 75dB More than 73dBµ emfIntermodulationMore than 75dB More than	GENERAL		
CH70 AIS1, 2156.525MHzUsable channelsUSA, CAN, INT, WX channelsType of emission16K0G3E (FM), 16K0G2B (DSC)Power supply requirement13.8V DC (11.7–15.9V DC)Current drain (at 13.8V DC) Tx 25W output5.5A 5.0A (RX hailer ON)Tx 25W output5.5AOperating temperature range Internal SP-20°C to $+60°C$ ; $-4°F to +140°FAntenna impedance50\Omega (SO-239)Weight (approx.)1400g; 3.09lbTRANSMITTER25W, 1WOutput power (at 13.8V DC)25W, 1WMax. frequency deviationErequency tolerance\pm 5.0\text{KHz}Frequency toleranceCH701st 30.15MHz, 2nd 450KHzRecEIVERIst 30.15MHz, 2nd 450KHzIntermediate frequencyCH70 (1% BER)Nore than 75dBMore than 75dBh$	Frequency range Tx	156.025-157.425MHz	
AIS1, 2161.975, 162.025MHzUsable channelsUSA, CAN, INT, WX channelsType of emission16K0G3E (FM), 16K0G2B (DSC)Power supply requirement13.8V DC (11.7–15.9V DC)Current drain (at 13.8V DC) Tx 25W output5.5ASx AF Max External SP Internal SP5.0A (RX hailer ON) 1.5AOperating temperature range-20°C to +60°C; $-4°F to +140°F$ Antenna impedance50 $\Omega$ (SO-239)Weight (approx.)1400g; 3.09lbTRANSMITTER00tput power (at 13.8V DC)Output power (at 13.8V DC)25W, 1WMax. frequency deviation±5.0KHzFrequency tolerance±10ppmSpurious emissionsLess than -70dBc (at 25W)Residual modulationMore than 40dBAdjacent channel powerMore than 70dBRECEIVERMore than 75dB More than 73dBµ emfIntermediate frequency CH70 (1% BER)More than 75dB More than 73dBµ emfIntermodulationMore than 75dB More than 73dBµ emfIntermodulationMore than 75dB More than 40dB	Rx	156.050-163.275MHz	
Usable channelsUSA, CAN, INT, WX channelsType of emission16K0G3E (FM), 16K0G2B (DSC)Power supply requirement13.8V DC (11.7–15.9V DC)Current drain (at 13.8V DC)5.5ATx 25W output5.5ARx AF Max External SP Internal SP5.0A (RX hailer ON) 1.5AOperating temperature range $-20^{\circ}$ C to +60°C; $-4^{\circ}$ F to +140°FAntenna impedance $50\Omega$ (SO-239)Weight (approx.)1400g; 3.09lbTRANSMITTER25W, 1WOutput power (at 13.8V DC)25W, 1WSpurious emissionsLess than -70dBc (at 25W)Residual modulationMore than 40dBAdjacent channel powerMore than 70dBRECEIVERMore than 70dBIntermediate frequency CH70 (1% BER)1st 30.15MHz, 2nd 450kHzSpurious response CH70 (1% BER)More than 73dBµ emfIntermodulationMore than 73dBµ emfIntermodulationMore than 73dBµ emfHum and noiseMore than 73dBµ emfAudio output powerMore than 15W with a 4 $\Omega$	CH70	156.525MHz	
ChannelschannelsType of emission16K0G3E (FM), 16K0G2B (DSC)Power supply requirement13.8V DC (11.7–15.9V DC)Current drain (at 13.8V DC)5.5ATx 25W output5.5ABx AF Max External SP Internal SP5.0A (RX hailer ON)Operating temperature range $-20^{\circ}C$ to $+60^{\circ}C$ ; $-4^{\circ}F$ to $\pm140^{\circ}F$ Antenna impedance $50\Omega$ (SO-239)Weight (approx.)1400g; 3.09lbTRANSMITTER25W, 1WOutput power (at 13.8V DC)25W, 1WSpurious emissionsLess than $-70dBc$ (at 25W)Residual modulationMore than 70dBRECEIVERIntermediate frequency CH70Intermediate frequency CH70 (1% BER)1st 30.15MHz, 2nd 450kHzSpurious response CH70 (1% BER)More than 75dB More than 73dBµ emfIntermodulationMore than 75dB More th	AIS1, 2	161.975, 162.025MHz	
Type of emission16K0G3E (FM), 16K0G2B (DSC)Power supply requirement13.8V DC (11.7–15.9V DC)Current drain (at 13.8V DC) $13.8V DC$ (11.7–15.9V DC)Tx 25W output $5.5A$ Rx AF Max External SP Internal SP $5.0A$ (RX hailer ON)Operating temperature range $-20^{\circ}C$ to $+60^{\circ}C$ ; $-4^{\circ}F$ to $+140^{\circ}F$ Antenna impedance $50\Omega$ (SO-239)Weight (approx.)1400g; 3.09lbTRANSMITTER $25W, 1W$ Output power (at 13.8V DC) $25W, 1W$ Max. frequency deviation $\pm 5.0$ kHzFrequency tolerance $\pm 10$ ppmSpurious emissionsLess than $-70dBc$ (at 25W)Residual modulationMore than 40dBAdjacent channel powerMore than 70dBRECEIVERIntermediate frequency CH70Intermediate sponse CH70 (1% BER)More than 73dBµ emfSpurious response CH70 (1% BER)More than 73dBµ emfIntermodulationMore than 75dB More than 73dBµ emfIntermodulationMore than 75dB More than	Usable channels	USA, CAN, INT, WX	
A16K0G2B (DSC)Power supply requirement13.8V DC (11.7–15.9V DC)Current drain (at 13.8V DC) $3.8V DC$ (11.7–15.9V DC)Tx 25W output $5.5A$ Rx AF Max External SP $5.0A$ (RX hailer ON)Internal SP $1.5A$ Operating temperature range $-20^{\circ}$ C to $+60^{\circ}$ C; $-4^{\circ}$ F to $+140^{\circ}$ FAntenna impedance $50\Omega$ (SO-239)Weight (approx.)1400g; 3.09lbTRANSMITTEROutput power (at 13.8V DC)25W, 1WMax. frequency deviation $\pm 5.0$ kHzFrequency tolerance $\pm 10pm$ Spurious emissionsLess than $-70dBc$ (at 25W)Residual modulationMore than 40dBAdjacent channel powerMore than 70dBRECEIVERIntermediate frequency CH70Intermediate requency Spurious response1st 30.15MHz, 2nd 450kHz 1st 21.7MHz, 2nd 450kHzSensitivity (at 12dB SINAD) $0.22\muV$ typicalAdjacent channel selectivity CH70 (1% BER)More than 75dB More than 73dBµ emfIntermodulationMore than 75dB More than 68dBµ emfIntermodulationMore than 40dBAdjacent channel selectivity CH70 (1% BER)More than 68dBµ emfIntermodulation CH70 (1% BER)More than 40dBAudio output powerMore than 15W with a 4 $\Omega$		channels	
Power supply requirement13.8V DC (11.7–15.9V DC)Current drain (at 13.8V DC) Tx 25W output5.5A 5.0A (RX hailer ON)Rx AF Max External SP Internal SP5.0A (RX hailer ON)Operating temperature range (approx.) $-20^{\circ}$ C to $+60^{\circ}$ C; $-4^{\circ}$ F to $+140^{\circ}$ FAntenna impedance $50\Omega$ (SO-239)Weight (approx.)1400g; 3.09lbTRANSMITTER0utput power (at 13.8V DC)Output power (at 13.8V DC)25W, 1WMax. frequency deviation Spurious emissions $\pm 5.0$ KHzFrequency tolerance CH70 $\pm 10$ ppmRecEIVER1st 30.15MHz, 2nd 450kHzIntermediate frequency CH701st 30.15MHz, 2nd 450kHzSensitivity (at 12dB SINAD) CH70 (1% BER)0.22µV typicalMore than 75dB More than 75dBHum and noiseMore than 15W with a 4 $\Omega$ <td>Type of emission</td> <td>16K0G3E (FM),</td>	Type of emission	16K0G3E (FM),	
Current drain (at 13.8V DC) Tx 25W outputTx 25W output $5.5A$ Bx AF Max External SP $5.0A$ (RX hailer ON)Internal SP $1.5A$ Operating temperature range $-20^{\circ}$ C to $+60^{\circ}$ C; $-4^{\circ}$ F to $+140^{\circ}$ FAntenna impedance $50\Omega$ (SO-239)Weight (approx.) $1400g$ ; $3.09lb$ TRANSMITTER $00tput$ power (at 13.8V DC)Output power (at 13.8V DC) $25W$ , $1W$ Max. frequency deviation $\pm 5.0kHz$ Frequency tolerance $\pm 10ppm$ Spurious emissionsLess than $-70dBc$ (at 25W)Residual modulationMore than 40dBAdjacent channel powerMore than 70dBRECEIVERIst 30.15MHz, 2nd 450kHzSensitivity (at 12dB SINAD) $0.22\muV$ typicalAdjacent channelMore than 75dBMore than 75dBMore than 73dB $\mu$ emfSpurious responseMore than 75dBCH70 (1% BER)More than 75dBMore than 75dBMore than 75dBMore than 75dBMore than 68dB $\mu$ emfHum and noiseMore than 40dBAudio output powerMore than 15W with a 4 $\Omega$		16K0G2B (DSC)	
Tx25W output Rx5.5A S.0ARxAF MaxExternal SP Internal SP5.0AOperating temperature range -20°C to +60°C; -4°F to +140°F-20°C to +60°C; -4°F to +140°FAntenna impedance $50\Omega$ (SO-239)Weight (approx.)1400g; 3.09lbTRANSMITTER0Output power (at 13.8V DC)25W, 1WSpurious emissionsLess than -70dBc (at 25W)Residual modulationMore than 40dBAdjacent channel powerMore than 70dBRECEIVERIst 30.15MHz, 2nd 450kHzSensitivity (at 12dB SINAD) $0.22\muV$ typicalAdjacent channel selectivity CH70 (1% BER)More than 75dB More than 75dB M	Power supply requirement	13.8V DC (11.7–15.9V DC)	
$\begin{array}{c c} \text{Rx AF Max External SP} & 5.0A (\text{RX hailer ON}) \\ \text{Internal SP} & 1.5A \\ \hline \\ \text{Operating temperature range} & -20^{\circ}\text{C to} +60^{\circ}\text{C}; \\ -4^{\circ}\text{F to} +140^{\circ}\text{F} \\ \hline \\ \text{Antenna impedance} & 50\Omega (\text{SO-239}) \\ \hline \\ \text{Weight (approx.)} & 1400g; 3.09lb \\ \hline \\ \hline \\ \text{TRANSMITTER} \\ \hline \\ \text{Output power (at 13.8V DC)} & 25W, 1W \\ \hline \\ \text{Max. frequency deviation} & \pm 5.0\text{kHz} \\ \hline \\ \text{Frequency tolerance} & \pm 10\text{ppm} \\ \hline \\ \text{Spurious emissions} & \text{Less than} -70dBc (at 25W) \\ \hline \\ \text{Residual modulation} & \text{More than 70dB} \\ \hline \\ \hline \\ \text{RECEIVER} \\ \hline \\ \hline \\ \text{Intermediate frequency} \\ \text{CH70} & 1st 30.15\text{MHz}, 2nd 450\text{kHz} \\ \hline \\ \text{Sensitivity (at 12dB SINAD)} & 0.22\text{V typical} \\ \hline \\ \text{Adjacent channel} \\ \text{Spurious response} \\ \hline \\ \text{CH70} & (1\% \text{ BER)} \\ \hline \\ \text{Nore than 75dB} \\ \hline \\ \text{More than 75dB} \\ \hline \\ \hline \\ \hline \\ \text{More than 75dB} \\ \hline \\ \hline \\ \hline \\ \hline \\ \hline \\ \text{Hum and noise} \\ \hline \\ \hline \\ More than 15W with a 4\Omega \\ \hline \\ $	Current drain (at 13.8V DC)		
$\begin{tabular}{ c c c c c } \hline Iternal SP & 1.5A & -20^\circ C to +60^\circ C; & -4^\circ F to +140^\circ F & -40^\circ F to +140^\circ F & -40^\circ F to +140^\circ F & -40^\circ F & to +140^\circ F & to +160^\circ F & to$	Tx 25W output	5.5A	
$\begin{array}{llllllllllllllllllllllllllllllllllll$	Rx AF Max External SP	5.0A (RX hailer ON)	
$\begin{array}{c c} -4^\circ F \ to +140^\circ F \\ \hline \\ \hline \\ \hline Antenna impedance & 50\Omega \ (SO-239) \\ \hline \\ $	Internal SP	1.5A	
Antenna impedance         50Ω (SO-239)           Weight (approx.)         1400g; 3.09lb           TRANSMITTER         25W, 1W           Output power (at 13.8V DC)         25W, 1W           Max. frequency deviation         ±5.0kHz           Frequency tolerance         ±10ppm           Spurious emissions         Less than -70dBc (at 25W)           Residual modulation         More than 40dB           Adjacent channel power         More than 70dB           RECEIVER         Intermediate frequency CH70         1st 30.15MHz, 2nd 450kHz           Sensitivity (at 12dB SINAD)         0.22µV typical           Adjacent channel         More than 75dB           Selectivity CH70 (1% BER)         More than 73dBµ emf           Intermodulation         More than 75dB           More than 75dB         More than 75dB           CH70 (1% BER)         More than 75dB           More than 68dBµ emf         More than 68dBµ emf           Intermodulation         More than 68dBµ emf           Hum and noise         More than 15W with a 4Ω	Operating temperature range	-20°C to +60°C;	
Weight (approx.)       1400g; 3.09lb         TRANSMITTER       25W, 1W         Output power (at 13.8V DC)       25W, 1W         Max. frequency deviation       ±5.0kHz         Frequency tolerance       ±10ppm         Spurious emissions       Less than -70dBc (at 25W)         Residual modulation       More than 40dB         Adjacent channel power       More than 70dB         RECEIVER       Intermediate frequency CH70       1st 30.15MHz, 2nd 450kHz         Sensitivity (at 12dB SINAD)       0.22µV typical         Adjacent channel       More than 75dB         Selectivity CH70 (1% BER)       More than 73dBµ emf         Intermodulation       More than 75dB         CH70 (1% BER)       More than 75dB         More than 75dB       More than 75dB         CH70 (1% BER)       More than 68dBµ emf         Intermodulation       More than 68dBµ emf         Hum and noise       More than 15W with a 4Ω		-4°F to +140°F	
TRANSMITTER           Output power (at 13.8V DC)         25W, 1W           Max. frequency deviation         ±5.0kHz           Frequency tolerance         ±10ppm           Spurious emissions         Less than -70dBc (at 25W)           Residual modulation         More than 40dB           Adjacent channel power         More than 70dB           RECEIVER         Intermediate frequency           Intermediate SiNAD)         0.22μV typical           Adjacent channel         More than 75dB           Sensitivity (at 12dB SINAD)         0.22μV typical           Adjacent channel         More than 75dB           Selectivity CH70 (1% BER)         More than 75dB           Spurious response         More than 75dB           CH70 (1% BER)         More than 75dB           Intermodulation         More than 75dB           More than 75dB         More than 75dB           CH70 (1% BER)         More than 68dBµ emf           Hum and noise         More than 40dB           Audio output power         More than 15W with a 4Ω	Antenna impedance	50Ω (SO-239)	
Output power (at 13.8V DC)         25W, 1W           Max. frequency deviation         ±5.0kHz           Frequency tolerance         ±10ppm           Spurious emissions         Less than -70dBc (at 25W)           Residual modulation         More than 40dB           Adjacent channel power         More than 70dB           RECEIVER         Intermediate frequency           Intermediate frequency         1st 30.15MHz, 2nd 450kHz           Sensitivity (at 12dB SINAD)         0.22µV typical           Adjacent channel         More than 75dB           Selectivity         CH70 (1% BER)           Spurious response         More than 75dB           CH70 (1% BER)         More than 75dB           Intermodulation         More than 75dB           More than 75dB         More than 75dB           CH70 (1% BER)         More than 68dBµ emf           Intermodulation         More than 68dBµ emf           Hum and noise         More than 15W with a 4Ω	Weight (approx.)	1400g; 3.09lb	
Max. frequency deviation         ±5.0kHz           Frequency tolerance         ±10ppm           Spurious emissions         Less than -70dBc (at 25W)           Residual modulation         More than 40dB           Adjacent channel power         More than 70dB           RECEIVER         Intermediate frequency CH70         1st 30.15MHz, 2nd 450kHz           Sensitivity (at 12dB SINAD)         0.22μV typical           Adjacent channel         More than 75dB           Selectivity         CH70 (1% BER)           Spurious response CH70 (1% BER)         More than 75dB           Intermodulation         More than 75dB           More than 75dB         More than 75dB           Spurious response         More than 75dB           CH70 (1% BER)         More than 75dB           More than 68dBµ emf         More than 68dBµ emf           Hum and noise         More than 15W with a 4Ω	TRANSMITTER		
Frequency tolerance         ±10pm           Spurious emissions         Less than -70dBc (at 25W)           Residual modulation         More than 40dB           Adjacent channel power         More than 70dB <b>RECEIVER</b> Intermediate frequency CH70         1st 30.15MHz, 2nd 450kHz           Sensitivity (at 12dB SINAD)         0.22μV typical           Adjacent channel         More than 75dB           selectivity CH70 (1% BER)         More than 75dB           Spurious response         More than 75dB           CH70 (1% BER)         More than 75dB           Intermodulation         More than 75dB           More than 75dB         More than 75dB           CH70 (1% BER)         More than 75dB           More than 75dB         More than 75dB           CH70 (1% BER)         More than 75dB           More than 48dB         More than 48dB           Audio output power         More than 15W with a 4Ω	Output power (at 13.8V DC)	25W, 1W	
Spurious emissions         Less than -70dBc (at 25W)           Residual modulation         More than 40dB           Adjacent channel power         More than 70dB           RECEIVER         Intermediate frequency CH70         1st 30.15MHz, 2nd 450kHz           Sensitivity (at 12dB SINAD)         0.22µV typical           Adjacent channel         More than 75dB           selectivity         CH70 (1% BER)           Spurious response         More than 75dB           CH70 (1% BER)         More than 75dB           Intermodulation         More than 75dB           CH70 (1% BER)         More than 68dBµ emf           Hum and noise         More than 40dB           Audio output power         More than 15W with a 4Ω	Max. frequency deviation	±5.0kHz	
Residual modulation         More than 40dB           Adjacent channel power         More than 70dB           RECEIVER         Intermediate frequency CH70         1st 30.15MHz, 2nd 450kHz           Sensitivity (at 12dB SINAD)         0.22µV typical           Adjacent channel selectivity         More than 75dB           Spurious response CH70 (1% BER)         More than 75dB           Nore than 75dB         More than 75dB           More than 75dB         More than 75dB           CH70 (1% BER)         More than 75dB           Intermodulation         More than 68dBµ emf           Hum and noise         More than 40dB           Audio output power         More than 15W with a 4Ω	Frequency tolerance	±10ppm	
Adjacent channel power         More than 70dB           RECEIVER         Intermediate frequency CH70         1st 30.15MHz, 2nd 450kHz           Sensitivity (at 12dB SINAD)         0.22μV typical           Adjacent channel selectivity         More than 75dB           Spurious response CH70 (1% BER)         More than 73dBµ emf           Intermodulation CH70 (1% BER)         More than 75dB           More than 75dB         More than 75dB           More than 75dB         More than 75dB           Adjacent of the component of t	Spurious emissions	Less than -70dBc (at 25W)	
RECEIVER           Intermediate frequency CH70         1st 30.15MHz, 2nd 450kHz           Sensitivity (at 12dB SINAD)         0.22μV typical           Adjacent channel selectivity         More than 75dB More than 73dBµ emf           Spurious response CH70 (1% BER)         More than 73dBµ emf           Intermodulation CH70 (1% BER)         More than 75dB More than 75dB           More than 75dB         More than 75dBµ emf           Intermodulation CH70 (1% BER)         More than 68dBµ emf           Hum and noise         More than 40dB           Audio output power         More than 15W with a 4Ω	Residual modulation	More than 40dB	
Intermediate frequency CH70         1st 30.15MHz, 2nd 450kHz           Sensitivity (at 12dB SINAD)         0.22μV typical           Adjacent channel selectivity         More than 75dB           Spurious response CH70 (1% BER)         More than 73dBµ emf           More than 73dBµ emf         More than 73dBµ emf           Intermodulation CH70 (1% BER)         More than 75dB           More than 75dB         More than 75dBµ emf           Intermodulation         More than 68dBµ emf           Hum and noise         More than 40dB           Audio output power         More than 15W with a 4Ω	Adjacent channel power	More than 70dB	
CH70         1st 21.7MHz, 2nd 450kHz           Sensitivity (at 12dB SINAD)         0.22μV typical           Adjacent channel         More than 75dB           selectivity CH70 (1% BER)         More than 75dB           Spurious response         More than 73dBµ emf           CH70 (1% BER)         More than 73dBµ emf           Intermodulation         More than 75dB           CH70 (1% BER)         More than 73dBµ emf           Hum and noise         More than 40dB           Audio output power         More than 15W with a 4Ω	RECEIVER		
CH70         1st 21.7MHz, 2nd 450kHz           Sensitivity (at 12dB SINAD)         0.22μV typical           Adjacent channel         More than 75dB           selectivity CH70 (1% BER)         More than 75dB           Spurious response         More than 73dBµ emf           CH70 (1% BER)         More than 73dBµ emf           Intermodulation         More than 75dB           CH70 (1% BER)         More than 73dBµ emf           Hum and noise         More than 40dB           Audio output power         More than 15W with a 4Ω	Intermediate frequency	1st 30.15MHz, 2nd 450kHz	
Adjacent channel         More than 75dB           selectivity         CH70 (1% BER)         More than 73dBµ emf           Spurious response         More than 75dB           CH70 (1% BER)         More than 75dB           Intermodulation         More than 75dB           CH70 (1% BER)         More than 68dBµ emf           Hum and noise         More than 40dB           Audio output power         More than 15W with a 4Ω			
selectivity         CH70 (1% BER)         More than 73dBμ emf           Spurious response CH70 (1% BER)         More than 75dB More than 73dBμ emf           Intermodulation CH70 (1% BER)         More than 68dBμ emf           Hum and noise         More than 40dB           Audio output power         More than 15W with a 4Ω	Sensitivity (at 12dB SINAD)	0.22µV typical	
Spurious response CH70 (1% BER)         More than 75dB More than 73dBµ emf           Intermodulation CH70 (1% BER)         More than 75dB More than 75dB           Hum and noise         More than 48dBµ emf           Audio output power         More than 15W with a 4Ω	Adjacent channel	More than 75dB	
CH70 (1% BER)         More than 73dBμ emf           Intermodulation         More than 75dB           CH70 (1% BER)         More than 68dBμ emf           Hum and noise         More than 40dB           Audio output power         More than 15W with a 4Ω	selectivity CH70 (1% BER)	More than 73dBµ emf	
CH70 (1% BER)         More than 73dBμ emf           Intermodulation         More than 75dB           CH70 (1% BER)         More than 68dBμ emf           Hum and noise         More than 40dB           Audio output power         More than 15W with a 4Ω	Spurious response	More than 75dB	
CH70 (1% BER)         More than 68dBμ emf           Hum and noise         More than 40dB           Audio output power         More than 15W with a 4Ω		More than 73dBµ emf	
$\begin{tabular}{lllllllllllllllllllllllllllllllllll$	Intermodulation	More than 75dB	
Audio output powerMore than 15W with a $4\Omega$	CH70 (1% BER)	More than 68dBµ emf	
	Hum and noise	More than 40dB	
	Audio output power	More than 15W with a $4\Omega$	
	(at 10% distortion)	RX speaker	

Measurements made in accordance with TIA/EIA 603 and IEC 62238. All stated specifications are subject to change without notice or obligation.

#### Applicable U.S. Military Specifications

The IC-M506 and HM-205B/RM have been tested to and passed the following MIL-STD requirements and strict environmental standards.

Standard	MIL 810 G		
Standard	Method	Procedure	
Low Pressure	500.5	I, II	
High Temperature	501.5	I, II	
Low Temperature	502.5	I, II	
Temperature Shock	503.5	I-C	
Solar Radiation	505.5	I	
Rain	506.5	I	
Humidity	507.5	II	
Salt Fog	509.5	-	
Dust Blowing	510.5	I	
Immersion	512.5	I	
Vibration	514.6	I	
Shock	516.6	I, IV	

Also meets equivalent MIL-STD-810-C, -D, -E and -G.

#### **Applicable IP Rating**

ss Protection St Water IPX8 (1 m depth water for 60 minutes)

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia and/or other countries. COMMANDMIC, AQUAQUAKE, MarineCommander and SUBMERSIBLE PLUS are trademarks of Icom Inc. (Japan) in the United States, NMEA 2000 is a trademark of the National Maritime Electronics Association. Inc. All other trademarks are the properties of their respective holders.

ICOM Inc. 1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

#### Icom America Inc.

12421 Willows Road NE. Kirkland, WA 98034, U.S.A. Phone : +1 (425) 454-8155 Fax : +1 (425) 454-1509 E-mail : sales@icomamerica.com URL : http://www.icomamerica.com

#### Icom Canada

Glenwood Centre #150-6165 Highway 17A, Delta, B.C., V4K 5B8, Canada Phone : +1 (604) 952-4266 Fax : +1 (604) 952-0090 E-mail : info@icomcanada.com URL : http://www.icomcanada.com

#### Icom Brazil

Rua Itororó, 444 Padre Eustáquio Belo Horizonte MG, CEP: 30130-150, Brazil Phone : +55 (31) 3582 8847 Fax : +55 (31) 3582 8987 E-mail : sales@icombrazil.com

#### Icom (Europe) GmbH Communication Equipment

Auf der Krautweide 24 65812 Bad Soden am Taunus, Germany Phone : +49 (6196) 76685-0 Fax : : +49 (6196) 76685-50 E-mail : info@icomeurope.com : http://www.icomeurope.com URL

#### Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer" Bajos A 08174, Sant Cugat del Valles, Barcelona Spain Barcelona, Spain Phone : +34 (93) 590 26 70 Fax : +34 (93) 589 04 46 E-mail : icom@icomspain.com URL : http://www.icomspain.com

#### Icom Polska Sp. Z o.o.

80-286 Gdansk, Jaskowa Dolina St. 75, Poland Phone : +48 (58) 551 0484 Fax : +48 (58) 551 4720 E-mail : icompolska@icompolska.com.pl URL : http://www.icompolska.com.pl

#### Icom (UK) Ltd.

Blacksole House, Altira Park Herne Bay, Kent, CT6 6GZ, U.K. Phone : +44 (0) 1227 741741 Fax : +44 (0) 1227 741742 E-mail : info@icomuk.co.uk URL : http://www.icomuk.co.uk

#### Icom France s.a.s.

Zac de la Plaine, 1 Rue Brindejonc des Moulinais, BP 45804, 31505 Toulouse Cedex 5, France Phone: +33 (5) 61 36 03 03 Fax : +33 (5) 61 36 03 00 E-mail : icom@icom-france.com URL : http://www.icom-france.co

#### Icom (Australia) Pty. Ltd. Unit 1 / 103 Garden Road, Clayton, VIC 3168 Australia Phone : +61 (03) 9549 7500 Fax : +61 (03) 9549 7505

E-mail : sales@icom.net.au URL : http://www.icom.net.au

#### Icom New Zealand 146A Harris Road, East Tamaki, Auckland, New Zealand Phone : +64 (09) 274 4062 Fax : +64 (09) 274 4708

E-mail : inquiries@icom.co.nz

URL : http://www.icom.co.nz

Asia Icom Inc. GF No. 68, Sec. 1 Cheng-Teh Road, Taipei, Taiwan, R.O.C. Phone :+886 (02) 2559 1899 Fax :+886 (02) 2559 1874 E-mail : sales @ asia-icom.com UBL : http://www.asia-icom.com

#### Your local distributor/dealer:

\*2 Optional UX-231 is required for AIS receiver.



OPTIONS Some options may not be available in some countries. Please ask your dealer for details

HM-195SW

(Super white)

SPEAKER-MICROPHONE

COMMANDMIC

HM-195B

(Black)

EXTENSION CABLE for

COMMANDMIC, HM-195B/SW

Count on us!

## **C-M506**

Supplied accessories

• 6.1m (20ft) of cable • Microphone hanger

VOICE SCRAMBLER

UNIT

· Mounting base for connector

FLUSH MOUNT KITS

# www.icom.co.jp/world