O ICOM

VHF MARINE TRANSCEIVER

IC-M605

2 ABC

5 JKL

8 TUV

0

4 GHI

7 PQRS

10

16/C

VOL/SC

3 DEF

6 MNO

9 WXYZ

20

C

Premium Class D DSC VHF Radio and System Flexibility

ГСОМ

N-UP

A

DISTRESS

3 nm

Range

VHF MARINE IC-M605

11

STBY

CALLING

1

123456789

ENT

CLR

Suu au au au au

MENU

CH/ENT

This VHF/AIS Radio Matches Your Boat in Performance, System Flexibility and User-Friendliness



Wide Viewing Angle 4.3-inch Color TFT LCD High I

First in its class, the color LCD provides nearly a 180 degree viewing angle. The 4.3-inch wide display has high resolution characters and function icons. The night mode screen provides the optimal viewing brightness for comfortable operation in the dark.

Night mode



Menu screen





Integrated AIS* Receiver

* An optional UX-251 AIS receiver unit is required, depending on version

AIS plotte



TARGET LIST (136)

AIS target list

With an integrated AIS receiver, the IC-M605 can show real-time AIS

vessel traffic information on the display. The AIS combo screen

enables you to monitor the AIS plotter during basic operation. You can directly

call a selected AIS target from the AIS screen using an individual DSC call.



Intuitive User Interface

A combination of the directional keypad and soft keys provides simple operation. Most used functions are assigned to soft keys (at the bottom of the display) for quick one push function access. The large ten-key pad enables you to smoothly enter channel numbers, MMSI numbers with ID names and so on.



Class Leading Receiver Performance

A weak signal adjacent to a strong signal can be clearly received by the IC-M605. Its commercial grade receiver performance (selectivity and IMD: more than 80 dB) provides reliable communication at all times.



Active Noise Canceling

The Active Noise Canceling digitally removes background noise from both transmit and receive audio and provides clear communication in a noisy maritime environment.



Last Call Voice Recording

The last call voice recording function automatically saves up to two minutes of an incoming call. Don't miss any incoming messages.



Private Conversation

With an optional voice scrambler unit, UT-112, the IC-M605 provides 32 tone secure conversation. This function is useful when you want to share private information with consort ships.

VHF MARINE TRANSCEIVER IC-M605

ÎCOM

DUAL 16 25°48.3000N

80°12.6000W

OCT 16 12:34

25W USA STBY RT DSC





Provides Clear, Loud Audio

The IC-M605's internal speaker enhances intelligibility of received calls. The waterproof, paper speaker-cone provides superior sound quality with a wide frequency range and a flat frequency response for powerful, yet clear audio.



Integrated GNSS Receiver

The GNSS (GPS, GLONASS and SBAS) receiver is integrated in the IC-M605. Position information can be simply received with connection to the supplied GNSS antenna with 5 m cable, UX-241.



30 W Two-Way Hailer and Automatic Foghorn

When connected to the optional horn speaker, SP-37, you can talk with crews on the deck or shore from the radio's microphone and can hear any reply via the horn speaker. Also available the RX hailer function and four patterns of automatic foghorn.



■■■ NMEA 2000[™], NMEA 0183/-HS Connectivity

Using NMEA 2000[™] connectivity, the radio can exchange GNSS, AIS reports, DSC call information data, radio frequency and PGN list data on the network. NMEA 0183/-HS GNSS position data can also be converted to NMEA 2000[™] data for other equipment.

And more

- IPX8 submersible (1 m depth of water for 60 minutes)
- Dual and Tri-watch functions Weather channels with alert function
- DSC Multi-task function
 • AquaQuake[™] draining function
- Instant-access button for Channel 16 and call channel
- Supplied speaker microphone, HM-205RB can be connected to the rear panel
- Compatible with the Icom's marine navigation system, MarineCommander™



VHF MARINE TRANSCEIVER

C-M605

CONVERSION CABLE

12-pin to 8-pin Required

AIS RECEIVER UNIT

UX-251

Already installed

depending on version.

CABLES for COMMAND HEAD/COMMANDMIC™

for COMMANDMIC[™].

OPC-2384

EXTENSION CABLE

OPC-1541

6.1 m (20 ft)

OPC-2377

UX-241

DC power

Count on us!

Microphone

10 m (32.8 ft).

Up to four cables available.

GNSS ANTENNA

Same as supplied.

Up to two cables available.

EXTENSION CABLE

Some options may not be available in some countries. Please ask your dealer for details.

?//

Supplied accessories

FLUSH MOUNT KIT

MB-75

OPC-2383, 10 m (32.8 ft) cable • Speaker

MIC hanger
Mobile bracket kit

90

microphone, HM-205RB • DC power cable

Supplied accessories

OPC-1540. 6.1 m (20 ft) cable
Microphone hanger

Mounting base for connector

Amber backlit COMMANDMIC

HM-195B/SW are also available



GENERALIs6.025-161.600 MHzFrequency rangeTx156.050-163.275 MHzRx156.050-163.275 MHzAIS1, 2161.975, 162.025 MHzUsable channelsUSA, CAN, INT, WX channelsType of emission16K0G3E (FM), 16K0G2B (DSC)Power supply requirement13.8 V DC (11.7-15.9 V DC)Current drain Tx25 W outputRx Max. audio8.0 AOperating temperature range-20°C to +60°C; -4°F to +140°FAntenna impedance50 Ω (S0-239)Weight (approximately)1510 g; 3.3 lbTRANSMITTER0utput power (at 13.8 V DC)Output power (at 13.8 V DC)25 W, 1 WMax. frequency deviation±5 kHzFrequency tolerance±5 ppmSpurious emissionsLess than -70 dBc (at 25 W)Residual modulationMore than 40 dBAdjacent channel powerMore than 70 dBRECEIVERIntermediate frequency CH70 (1% BER)Adjacent channel selectivity CH70 (1% BER)More than 80 dB More than 80 dB CH70 (1% BER)Adjacent channel selectivity CH70 (1% BER)More than 73 dBµ emfIntermedulationMore than 73 dBµ emfIntermodulationMore than 73 dBµ emfIntermodulationMore than 73 dBµ emfIntermodulationMore than 15 W with a 4 Ω (at 10% distortion)	SPECIFICATIONS	
Rx CH70 AIS1, 2156.050–163.275 MHz 156.525 MHz 161.975, 162.025 MHzUsable channelsUSA, CAN, INT, WX channelsType of emission16K0G3E (FM), 16K0G2B (DSC)Power supply requirement13.8 V DC (11.7–15.9 V DC)Current drain Tx 25 W output Rx Max. audio6.0 A 8.0 AOperating temperature range Antenna impedance -20° C to $+60^{\circ}$ C; -4° F to $+140^{\circ}$ FAntenna impedance50 Ω (SO-239)Weight (approximately)1510 g; 3.3 lbTRANSMITTER0utput power (at 13.8 V DC)Output power (at 13.8 V DC)25 W, 1 WMax. frequency deviation ± 5 kHzFrequency tolerance ± 5 ppmSpurious emissionsLess than -70 dBc (at 25 W)Residual modulationMore than 40 dBAdjacent channel powerMore than 70 dBRECEIVERIntermediate frequency CH70 (1% BER)Adjacent channel selectivity CH70 (1% BER)0.71 µV emf typicalAdjacent channel selectivity CH70 (1% BER)More than 80 dB More than 80 dB More than 80 dB µ emfSpurious response CH70 (1% BER)More than 73 dBµ emfIntermedulationMore than 73 dBµ emfIntermodulationMore than 73 dBµ emfHum and noiseMore than 40 dBAudio output powerMore than 15 W with a 4 Ω	GENERAL	
$\begin{tabular}{ c c c c c c c c c c c c c c c c c c c$	Frequency range Tx	156.025–161.600 MHz
AIS1, 2161.975, 162.025 MHzUsable channelsUSA, CAN, INT, WX channelsType of emission16K0G3E (FM), 16K0G2B (DSC)Power supply requirement13.8 V DC (11.7–15.9 V DC)Current drain Tx 25 W output Rx Max. audio8.0 AOperating temperature range -20° C to $+60^{\circ}$ C; -4° F to $+140^{\circ}$ FAntenna impedance50 Ω (SO-239)Weight (approximately)1510 g; 3.3 lbTRANSMITTER0Output power (at 13.8 V DC)25 W, 1 WMax, frequency deviation ± 5 HzFrequency tolerance ± 5 ppmSpurious emissionsLess than -70 dBc (at 25 W)Residual modulationMore than 40 dBAdjacent channel powerMore than 70 dBRECEIVER0.71 µV emf typicalIntermediate frequency CH70 (1% BER)0.71 µV emf typicalAdjacent channel selectivity CH70 (1% BER)More than 80 dB More than 80 dB More than 73 dBµ emfIntermodulationMore than 73 dBµ emfIntermodulationMore than 73 dBµ emfHum and noiseMore than 40 dBAudio output powerMore than 15 W with a 4 Ω		156.050–163.275 MHz
Usable channelsUSA, CAN, INT, WX channelsType of emission16K0G3E (FM), 16K0G2B (DSC)Power supply requirement13.8 V DC (11.7–15.9 V DC)Current drain Tx 25 W output Rx Max. audio $6.0 A$ 8.0 AOperating temperature range -20°C to +60°C; -4°F to +140°FAntenna impedance 50Ω (SO-239)Weight (approximately)1510 g; 3.3 lb TRANSMITTER Dutput power (at 13.8 V DC)Output power (at 13.8 V DC) $25 W$, 1 WMax. frequency deviation $\pm 5 \text{ kHz}$ Frequency tolerance $\pm 5 \text{ ppm}$ Spurious emissionsLess than -70 dBc (at 25 W)Residual modulationMore than 40 dBAdjacent channel powerMore than 70 dB RECEIVER 0.71 µV emf typicalAdjacent channel selectivity CH70 (1% BER)0.71 µV emf typicalAdjacent channel selectivity CH70 (1% BER)More than 80 dB More than 80 dB More than 73 dBµ emfIntermodulationMore than 73 dBµ emfIntermodulationMore than 73 dBµ emfHum and noiseMore than 40 dBAdudio output powerMore than 15 W with a 4 Ω	CH70	156.525 MHz
Type of emission16K0G3E (FM), 16K0G2B (DSC)Power supply requirement13.8 V DC (11.7–15.9 V DC)Current drain Tx 25 W output6.0 ARx Max. audio8.0 AOperating temperature range -20° C to $+60^{\circ}$ C; -4° F to $+140^{\circ}$ FAntenna impedance50 Ω (SO-239)Weight (approximately)1510 g; 3.3 lb TRANSMITTER 0utput power (at 13.8 V DC)Output power (at 13.8 V DC)25 W, 1 WMax. frequency deviation ± 5 kHzFrequency tolerance ± 5 ppmSpurious emissionsLess than -70 dBc (at 25 W)Residual modulationMore than 40 dBAdjacent channel powerMore than 70 dB RECEIVER 0.71 µV emf typicalIntermediate frequency CH70 (1% BER)0.71 µV emf typicalAdjacent channel selectivity CH70 (1% BER)More than 80 dB More than 80 dB More than 80 dB µ emfSpurious response CH70 (1% BER)More than 73 dBµ emfIntermodulationMore than 73 dBµ emfIntermodulationMore than 73 dBµ emfHum and noiseMore than 40 dBAudio output powerMore than 15 W with a 4 Ω	AIS1, 2	161.975, 162.025 MHz
Power supply requirement13.8 V DC (11.7–15.9 V DC)Current drain Tx 25 W output Rx Max. audio6.0 AOperating temperature range -20° C to $+60^{\circ}$ C; -4° F to $+140^{\circ}$ FAntenna impedance50 Ω (SO-239)Weight (approximately)1510 g; 3.3 lbTRANSMITTER0utput power (at 13.8 V DC)Output power (at 13.8 V DC)25 W, 1 WMax. frequency deviation ± 5 kHzFrequency tolerance ± 5 ppmSpurious emissionsLess than -70 dBc (at 25 W)Residual modulationMore than 40 dBAdjacent channel powerMore than 70 dBRECEIVER0.22 µV typicalIntermediate frequency CH70 (1% BER)0.71 µV emf typicalAdjacent channel selectivity CH70 (1% BER)More than 80 dB More than 80 dB µ emfSpurious response CH70 (1% BER)More than 73 dBµ emfIntermedulationMore than 73 dBµ emfIntermodulationMore than 73 dBµ emfHum and noiseMore than 40 dBAudio output powerMore than 15 W with a 4 Ω		
Current drainTx25 W output Rx6.0 A 8.0 AOperating temperature range Antenna impedance -20° C to $+60^{\circ}$ C; -4° F to $+140^{\circ}$ F Antenna impedance 50Ω (SO-239)Weight (approximately)1510 g; 3.3 lbTRANSMITTER25 W, 1 WOutput power (at 13.8 V DC)25 W, 1 WMax. frequency deviation ± 5 kHzFrequency tolerance ± 5 ppmSpurious emissionsLess than -70 dBc (at 25 W)Residual modulationMore than 40 dBAdjacent channel powerMore than 70 dBRECEIVER0.15 MHz, 450 kHz (1st/2nd) 21.70 MHz, 450 kHz (1st/2nd) 21.70 MHz, 450 kHz (1st/2nd)Gensitivity (at 12 dB SINAD)0.22 µV typicalAdjacent channel selectivityMore than 80 dB More than 80 dB More than 80 dB More than 73 dBµ emfIntermodulationMore than 73 dBµ emfHum and noiseMore than 40 dBAudio output powerMore than 15 W with a 4 Ω	Type of emission	
Rx Max. audio8.0 AOperating temperature range -20° C to $+60^{\circ}$ C; -4° F to $+140^{\circ}$ FAntenna impedance50 Ω (SO-239)Weight (approximately)1510 g; 3.3 lbTRANSMITTEROutput power (at 13.8 V DC)25 W, 1 WMax. frequency deviation ± 5 kHzFrequency tolerance ± 5 ppmSpurious emissionsLess than -70 dBc (at 25 W)Residual modulationMore than 40 dBAdjacent channel powerMore than 70 dBRECEIVER30.15 MHz, 450 kHz (1st/2nd) 21.70 MHz, 450 kHz (1st/2nd) 21.70 MHz, 450 kHz (1st/2nd)Sensitivity (at 12 dB SINAD)0.22 µV typicalCH70 (1% BER)More than 80 dB More than 80 dB CH70 (1% BER)Spurious response CH70 (1% BER)More than 73 dBµ emfIntermodulationMore than 73 dBµ emfIntermodulationMore than 73 dBµ emfHum and noiseMore than 40 dBAudio output powerMore than 15 W with a 4 Ω	Power supply requirement	13.8 V DC (11.7–15.9 V DC)
$\begin{array}{c c} \hline Operating temperature range & -20^{\circ}C to +60^{\circ}C; -4^{\circ}F to +140^{\circ}F\\ \hline Antenna impedance & 50 \ \Omega \ (SO-239)\\ \hline Weight (approximately) & 1510 \ g; 3.3 \ lb\\ \hline TRANSMITTER & \\ \hline Output power (at 13.8 V DC) & 25 W, 1 W\\ \hline Max. frequency deviation & \pm 5 \ Hz\\ \hline Frequency tolerance & \pm 5 \ ppm\\ \hline Spurious emissions & Less than -70 \ dBc \ (at 25 W)\\ \hline Residual modulation & More than 40 \ dB\\ \hline Adjacent channel power & More than 70 \ dB\\ \hline RECEIVER & \\ \hline Intermediate frequency & 30.15 \ MHz, 450 \ kHz \ (1st/2nd) \\ CH70 & 21.70 \ MHz, 450 \ kHz \ (1st/2nd) \\ CH70 \ (1\% \ BER) & 0.21 \ \muV \ emf \ typical \\ \hline Adjacent channel selectivity \\ Adjacent channel selectivity \\ CH70 \ (1\% \ BER) & More \ than 80 \ dB \\ \hline More \ than 73 \ dB\mu \ emf \\ \hline Intermodulation & More \ than 73 \ dB\mu \ emf \\ \hline Intermodulation & More \ than 73 \ dB\mu \ emf \\ \hline Hum \ and \ noise & More \ than 40 \ dB \\ \hline Audio output \ power & More \ than 15 \ W \ with a 4 \ \Omega \\ \hline \end{array}$	Current drain Tx 25 W output	6.0 A
Antenna impedance50 Ω (SO-239)Weight (approximately)1510 g; 3.3 lbTRANSMITTERImage: Construct of the system of the s	Rx Max. audio	
Weight (approximately) 1510 g; 3.3 lb TRANSMITTER 25 W, 1 W Output power (at 13.8 V DC) 25 W, 1 W Max. frequency deviation ±5 kHz Frequency tolerance ±5 ppm Spurious emissions Less than -70 dBc (at 25 W) Residual modulation More than 40 dB Adjacent channel power More than 70 dB RECEIVER 30.15 MHz, 450 kHz (1st/2nd) Intermediate frequency CH70 21.70 MHz, 450 kHz (1st/2nd) Sensitivity (at 12 dB SINAD) 0.22 μV typical OL770 (1% BER) More than 80 dB More than 80 dB More than 73 dBµ emf Intermodulation More than 73 dBµ emf Intermodulation More than 73 dBµ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω	Operating temperature range	-20°C to +60°C; -4°F to +140°F
TRANSMITTEROutput power (at 13.8 V DC)25 W, 1 WMax. frequency deviation ± 5 kHzFrequency tolerance ± 5 ppmSpurious emissionsLess than -70 dBc (at 25 W)Residual modulationMore than 40 dBAdjacent channel powerMore than 70 dBRECEIVERIntermediate frequencyIntermediate frequency30.15 MHz, 450 kHz (1st/2nd)CH7021.70 MHz, 450 kHz (1st/2nd)CH700.22 μ V typicalAdjacent channel selectivityMore than 80 dBMore than 80 dBMore than 80 dBCH70 (1% BER)More than 77 dBSpurious responseMore than 73 dBµ emfIntermodulationMore than 73 dBµ emfHum and noiseMore than 40 dBAudio output powerMore than 15 W with a 4 Ω	Antenna impedance	50 Ω (SO-239)
$\begin{array}{c c} \hline Output power (at 13.8 V DC) & 25 W, 1 W \\ \hline Max. frequency deviation & \pm 5 kHz \\ \hline Frequency tolerance & \pm 5 ppm \\ \hline Spurious emissions & Less than -70 dBc (at 25 W) \\ \hline Residual modulation & More than 40 dB \\ \hline Adjacent channel power & More than 70 dB \\ \hline \textbf{RECEIVER} & \\ \hline Intermediate frequency & 30.15 MHz, 450 kHz (1st/2nd) \\ CH70 & 21.70 MHz, 450 kHz (1st/2nd) \\ CH70 & 0.22 \muV typical \\ \hline Adjacent channel selectivity & More than 80 dB \\ \hline Adjacent channel selectivity & More than 80 dB \\ \hline CH70 (1\% BER) & More than 80 dB \\ CH70 (1\% BER) & More than 73 dB \mu emf \\ \hline Intermodulation & More than 73 dB \mu emf \\ \hline Intermodulation & More than 73 dB \mu emf \\ \hline Intermodulation & More than 73 dB \mu emf \\ \hline Hum and noise & More than 40 dB \\ \hline Audio output power & More than 15 W with a 4 \Omega \\ \hline \end{array}$	Weight (approximately)	1510 g; 3.3 lb
$\begin{array}{llllllllllllllllllllllllllllllllllll$	TRANSMITTER	
Frequency tolerance ±5 ppm Spurious emissions Less than -70 dBc (at 25 W) Residual modulation More than 40 dB Adjacent channel power More than 70 dB RECEIVER 30.15 MHz, 450 kHz (1st/2nd) Intermediate frequency 30.15 MHz, 450 kHz (1st/2nd) Sensitivity (at 12 dB SINAD) 0.22 μV typical CH70 (1% BER) 0.71 μV emf typical Adjacent channel selectivity More than 80 dB CH70 (1% BER) More than 80 dB Spurious response More than 77 dB CH70 (1% BER) More than 73 dBµ emf Intermodulation More than 73 dBµ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω	Output power (at 13.8 V DC)	25 W, 1 W
Spurious emissions Less than -70 dBc (at 25 W) Residual modulation More than 40 dB Adjacent channel power More than 70 dB RECEIVER 30.15 MHz, 450 kHz (1st/2nd) 21.70 MHz, 450 kHz (1st/2nd) Sensitivity (at 12 dB SINAD) 0.22 µV typical CH70 (1% BER) 0.71 µV emf typical Adjacent channel selectivity CH70 (1% BER) More than 80 dB More than 80 dBµ emf Spurious response CH70 (1% BER) More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 73 dBµ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω	Max. frequency deviation	±5 kHz
Residual modulation More than 40 dB Adjacent channel power More than 70 dB RECEIVER 30.15 MHz, 450 kHz (1st/2nd) 21.70 MHz, 450 kHz (1st/2nd) Intermediate frequency CH70 30.15 MHz, 450 kHz (1st/2nd) Sensitivity (at 12 dB SINAD) 0.22 µV typical CH70 (1% BER) 0.71 µV emf typical Adjacent channel selectivity CH70 (1% BER) More than 80 dB More than 80 dBµ emf Spurious response CH70 (1% BER) More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 73 dBµ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω	Frequency tolerance	±5 ppm
Adjacent channel power More than 70 dB RECEIVER 30.15 MHz, 450 kHz (1st/2nd) 21.70 MHz, 450 kHz (1st/2nd) 21.70 MHz, 450 kHz (1st/2nd) Sensitivity (at 12 dB SINAD) 0.22 μV typical CH70 (1% BER) 0.71 μV emf typical Adjacent channel selectivity CH70 (1% BER) More than 80 dB More than 80 dBµ emf Spurious response CH70 (1% BER) More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 73 dBµ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω	Spurious emissions	Less than -70 dBc (at 25 W)
RECEIVER 30.15 MHz, 450 kHz (1st/2nd) 21.70 MHz, 450 kHz (1st/2nd) Intermediate frequency CH70 30.15 MHz, 450 kHz (1st/2nd) 21.70 MHz, 450 kHz (1st/2nd) Sensitivity (at 12 dB SINAD) 0.22 μV typical CH70 (1% BER) 0.71 μV emf typical Adjacent channel selectivity CH70 (1% BER) More than 80 dB More than 80 dBµ emf Spurious response CH70 (1% BER) More than 77 dB More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 73 dBµ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω	Residual modulation	More than 40 dB
Intermediate frequency CH70 30.15 MHz, 450 kHz (1st/2nd) 21.70 MHz, 450 kHz (1st/2nd) Sensitivity (at 12 dB SINAD) 0.22 μV typical CH70 (1% BER) 0.71 μV emf typical Adjacent channel selectivity CH70 (1% BER) More than 80 dB More than 80 dBµ emf Spurious response CH70 (1% BER) More than 77 dB More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 73 dBµ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω	Adjacent channel power	More than 70 dB
CH70 21.70 MHz, 450 kHz (1st/2nd) Sensitivity (at 12 dB SINAD) 0.22 μV typical CH70 (1% BER) 0.71 μV emf typical Adjacent channel selectivity CH70 (1% BER) More than 80 dB More than 80 dBµ emf Spurious response CH70 (1% BER) More than 77 dB More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 73 dBµ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω	RECEIVER	
Sensitivity (at 12 dB SINAD) 0.22 μV typical CH70 (1% BER) 0.71 μV emf typical Adjacent channel selectivity CH70 (1% BER) More than 80 dB More than 80 dBµ emf Spurious response CH70 (1% BER) More than 77 dB More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 73 dBµ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω		30.15 MHz, 450 kHz (1st/2nd)
CH70 (1% BER) 0.71 μV emf typical Adjacent channel selectivity CH70 (1% BER) More than 80 dB More than 80 dBµ emf Spurious response CH70 (1% BER) More than 77 dB More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 73 dBµ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω	CH70	21.70 MHz, 450 kHz (1st/2nd)
Adjacent channel selectivity CH70 (1% BER) More than 80 dB More than 80 dBµ emf Spurious response CH70 (1% BER) More than 77 dB More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 80 dB More than 73 dBµ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω	Sensitivity (at 12 dB SINAD)	0.22 μV typical
CH70 (1% BER) More than 80 dBμ emf Spurious response CH70 (1% BER) More than 77 dB More than 73 dBμ emf Intermodulation CH70 (1% BER) More than 80 dB More than 80 dB Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω		0.71 μV emf typical
Spurious response CH70 (1% BER) More than 77 dB More than 73 dBµ emf Intermodulation CH70 (1% BER) More than 80 dB More than 73 dBµ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω		
CH70 (1% BER) More than 73 dBμ emf Intermodulation More than 80 dB CH70 (1% BER) More than 73 dBμ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω	CH70 (1% BER)	
Intermodulation CH70 (1% BER) More than 80 dB More than 73 dBμ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω		
CH70 (1% BER) More than 73 dBμ emf Hum and noise More than 40 dB Audio output power More than 15 W with a 4 Ω		1
Hum and noiseMore than 40 dBAudio output powerMore than 15 W with a 4 Ω		
Audio output powerMore than 15 W with a 4 Ω	. ,	1
(at 10% distortion) external speaker		
	(at 10% distortion)	external speaker

Measurements made in accordance with TIA/EIA 603 and IEC 62238. All stated specifications are subject to change without notice or obligation.

Applicable U.S. Military Specifications

Standard	MIL 810 G		
	Method	Procedure	
Low Pressure	500.5	I, II	
High Temperature	501.5	I, II	
Low Temperature	502.5	I, II	
Temperature Shock	503.5	I–C	
Solar Radiation	505.5	I	
Rain	506.5	Ι	
Humidity	507.5	II	
Salt Fog	509.5	-	
Dust Blowing	510.5	Ι	
Immersion	512.5	Ι	
Vibration	514.6	Ι	
Shock	516.6	I, IV	

Also meets equivalent MIL-STD-810-C, -D, -E and -F.

Applicable IP Rating

Ingress Protection Standard		
Water	IPX8 (1 m depth water for 60 minutes)	
Supplied accessories: • Speaker microphone, HM-205RB • GNSS antenna, UX-241		

Microphone hanger • DC power cable • Mounting bracket kit

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand and/or other countries. COMMANDMIC, AQUAQUAKE and MarineCommander are trademarks of Icom Inc. (Japan) in the United States. NMEA 2000 is a trademark of the National Maritime Electronics Association, Inc. All other trademarks are the properties of their respective holders.

28 (

ICOM Inc. 1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 www.icom.co.jp/world

Icom America Inc. 12421 Willows Road NE, Kirkland, WA 98034, U.S.A. Phone: +1 (425) 454-8155 Fax :+1 (425) 454-1509 E-mail :sale@icomamerica.com

URL : http://www.icomamerica.com

Icom Canada

Glenwood Centre #150-6165 Highway 17A, Delta, B.C., V4K 5B8, Canada Phone :+1 (604) 952-4266 Fax :+1 (604) 952-009 E-mail : info@icomcanada.com URL :http://www.icomcanada.com

Icom Brazil

Rua Itororó, 444 Padre Eustáquio Belo Horizonte MG, CEP: 30720-450, Brazil Phone: +55 (31) 3582 8847 Fax : +55 (31) 3582 8987 E-mail: sales@icombrazil.com

Icom (Europe) GmbH

Communication Equipment Auf der Krautweide 24 65812 Bad Soden am Taunus, Germany Phone : +49 (6196) 76685-0 Fax : +49 (6196) 76685-50 E-mail : info @icomeurope.com URL : http://www.icomeurope.com

Icom Spain S.L.

Ctra. Rubi, No. 88 "Editicio Can Castanyer" Bajos A 08174, Sant Cugat del Valles, Barcelona, Spain Phone: +34 (93) 590 26 70 Fax : +34 (93) 589 04 46 E-mail : icom@icomspain.com URL : http://www.icomspain.com

Icom (UK) Ltd.

Blacksole House, Attira Park, Herne Bay, Kent, CT6 6GZ, U.K. Phone : +44 (0) 1227 741741 Fax : +44 (0) 1227 741742 E-mail : info@icomuk.co.uk URL : http://www.icomuk.co.uk

Icom France s.a.s.

Zac de la Plaine, 1 Rue Brindejonc des Moulinais, BP 45804, 31505 Toulouse Cedex 5, France Phone : +33 (5) 61 36 03 03 Fax : +33 (5) 61 36 03 00 E-mail : icom @icom-france.com URL : http://www.icom-france.com

OPTIONS

COMMANDMIC™

HM-195GB

RC-M600

SP-37

SPEAKER-

HM-20588

Same as supplied

MICROPHONE

IPX8 submersible

HORN SPEAKER

(1 m depth of water for 60 min.)

COMMAND HEAD

(Black)

HM-195GW

VOICE SCRAMBLER

UT-11

CLASS B AIS TRANSPONDER

:25 (5.8)

UNIT

UT-112

MA-500TR

66.6.6.6

DIMENSIONS

250 (9.8)

0000

93.5 (3.7)

For transmitting own

vessel AIS information

Unit: mm (inch)

(White)

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road, Clayton, VIC 3168 Australia Phone : +61 (03) 9549 7500 Fax : +61 (03) 9549 7505 E-mail : sales@icom.net.au URL : http://www.icom.net.au

Icom New Zealand

39C Rennie Drive, Airport Oaks, Auckland, New Zealand Phone : +64 (09) 274 4062 Fax : +64 (09) 274 4708 E-mail : inquiries@icom.co.nz URL : http://www.icom.co.nz

Asia Icom Inc. 6F No. 68, Sec. 1 Cheng-Teh Road, Taipei, Taiwan, R.O.C.

Taipei, Taipei

Your local distributor/dealer:





REAR PANEL VIEW